

Why compromise, when you have a choice. Choose genuine. Say no to non-genuine.

Get Quality, Warranty, Durability, Longevity.













Cost Saving
Toner Box Technology

34 Pages Per Minute

Duplex Printing

250 Sheets Paper Tray

2,600 Pages Inbox Toner


Technical Specifications

	HL-B2000D
Key Functions	Automatic 2-sided Printing
PRINT FUNCTIONS	
Print Speed (A4/Letter)	Up to 34 / 36 ppm
2-sided Printing	Yes
Print Resolution	600 x 600 dpi; HQ1,200 (2,400 x 600 dpi) quality; 1,200 x 1,200 dpi
First Printout Time (Ready)	Less than 8.5 secs
Max. Monthly Duty Cycle	Up to 15,000 pages
PAPER HANDLING	
Input Capacity	250 sheets
Manual Feed Slot	1 sheet
Output Capacity [^]	150 Sheets Face Down
Media Weights	60 to 230g/m² (Using Manual Feed Slot)
Media Size	A4, Letter, A5, A5(Long Edge), A6, Executive, Legal, Folio, Mexico Legal, India Legal
CONNECTIVITY	
Interface	Hi-Speed USB 2.0
OTHERS	
Processor Speed	600MHz
Memory	32MB
OS Compatibility	Windows 7 SP1, 8, 8.1, 10, Server 2008, Server 2008 R2, Server 2012, Server 2012 R2, Server 2016, macOS v10.10.5, 10.11.x, 10.12.x (Download only), CUPS, LPD/LPRng (x86/x64 environment)
Energy Saving Mode	Energy Star
Power Consumption (Printing / Sleep)	510W / 5.7W
Power Source	220-240V, AC 50/60Hz
Noise Level	LpAm = 49 dB(A)
SUPPLIES	
Standard Yield Toner (TN-B021)*	Approx. 2,600 Pages
Drum (DR-B021)	Approx. 12,000 Pages
Inbox Toner	Approx. 2,600 Pages
DIMESIONS & WEIGHT	
Dimension (W x D X H)	356 x 360 x 183 mm
Weight	7.4kg

^{*}In accordance with ISO/IEC 19752 ^Actual output tray capacity may vary depending on environmental conditions

HEAD OFFICE: Brother International (India) Private Limited

Unit No.408, 4th Floor, B-Wing, 215 Atrium, Andheri-Kurla Road, Andheri (East), Mumbai 400093. Tel.: +91-22-66708900 I Fax: +91-22-66708999 Operating Hours: Mon to Fri (8.30 am to 6.30 pm) & Sat (9.00 am to 6.00 pm)



BANGALORE I CHENNAI I DELHI I KOLKATA I PUNE I LUCKNOW



Brother strongly recommends the use of genuine Brother consumable products only. Benefits include better quality print, greater yields per consumable, protection of your machine from damages and achievement of optimum performance. As a precaution, please note that your machine warranty may not cover any damages arising from the use of non-genuine consumables.